

NuMedia 2000 - Modem Setup

(for use ONLY with optional pre-programmed Dial-up/Cellular/RF modems)

- 1) Right click in the black of your simulation and select "Sign Properties"
- 2) Go to the "File Organization" tab, and check on the "Comm Device" option, then select "Modem"
- 3) Enter the Dial-Up "Phone Number" that the sign has been setup with. It is also suggested to add a "Long Comm Response" time of 18. This number can usually resolve issues with file info not being reported back into the "Sign Files" section accurately and/or improper "Current Sign Status" information. **NOTE FOR RF MODEMS ONLY-->** delete entries from the phone number, and all 3 'string' fields, and adjust the "Long Comm Response" field only.
NOTE--> if communications are cut off or very unstable, and not fully completed properly, could put your sign into a stopped status. A longer comm response setting should prevent this from occurring.
- 4) Select the "Ok" button and say "Yes" to save your settings.

